

Stabilizing Quantum States by Constructive Design of Open Quantum Dynamics

Francesco Ticozzi, Sophie G. Schirmer and Xiaoting Wang

Abstract—Based on recent work on the asymptotic behavior of controlled quantum Markovian dynamics, we show that any generic quantum state can be stabilized by devising constructively a simple Lindblad-GKS generator that can achieve global asymptotic stability at the desired state. The applicability of such result is demonstrated by designing a direct feedback strategy that achieves global stabilization of a qubit state encoded in a noise-protected subspace.

I. INTRODUCTION

The theory of open quantum dynamics has attracted significant interest recently due to the fast development of new experimental skills to study, and even design, the interaction between a quantum system and its environment. In many applications, the dynamics of an open system interacting with its reservoir can be described by a quantum Markov process. Specifically, let us consider a finite-dimensional quantum system described in a Hilbert space $\mathcal{H} \simeq \mathbb{C}^N$. The state of the system is represented by a *density operator* ρ on $\mathcal{H}$ with $\rho \geq 0$ and $\text{trace}(\rho) = 1$. Density operators form a convex set $\mathfrak{D}(\mathcal{H}) \subset \mathfrak{H}(\mathcal{H})$ with one-dimensional projectors corresponding to extreme points (*pure states*). We denote by $\mathfrak{B}(\mathcal{H})$ the set of linear operators on $\mathcal{H}$, with $\mathfrak{H}(\mathcal{H})$ denoting the real subspace of Hermitian operators. Throughout the paper we will use $\dagger$ to denote the adjoint, $*$ for the complex conjugate, and $[X, Y] = XY - YX$, $\{X, Y\} = XY + YX$ to represent the commutator and the anticommutator, respectively. The Markovian quantum dynamics is described by the following Lindblad-Gorini-Kossakowski-Sudarshan master equation (LME) [1], [2]:

$$\dot{\rho} = -i[H, \rho] + \mathcal{D}(L, \rho) = -i[H, \rho] + L\rho L^\dagger - \frac{1}{2}\{L^\dagger L, \rho\}, \quad (1)$$

where $H \in \mathfrak{H}(\mathcal{H})$ is the Hamiltonian and $L \in \mathfrak{B}(\mathcal{H})$ describes the dissipation due to the environment, accounting for the non-unitary part of the evolution.

The mathematical problem we consider is the following: *Find a pair (H, L) that makes a given density matrix ρ globally asymptotically stable (GAS) assuming dissipative dynamics of Lindblad type* (for the standard definition of GAS see [3]). This type of dynamic stabilization of quantum states is important in quantum information processing applications [4], [5]. The main result of this paper is a constructive procedure to design a pair (H, L) that renders an arbitrary mixed state ρ GAS. This problem of GAS has been considered before for pure states, i.e., rank-1 projectors [10], [6], [7]. Stabilizing pure states is an important task but it is not always possible to stabilize a desired pure state. However, there always exists a mixed state arbitrarily close to the target state that can be stabilized, hence attaining *practical stability*, that is, stability of a neighborhood of the target state. Mixed-state stabilization was considered in [8] but without a constructive procedure to find the required dynamics (H, L) . The L and H we explicitly construct in this Note are in a simple form in an eigenbasis of ρ , tri- and quintdiagonal, respectively,

F. Ticozzi is with the Dipartimento di Ingegneria dell'Informazione, Università di Padova, via Gradenigo 6/B, 35131 Padova, Italy (ticozzi@dei.unipd.it).

S. G. Schirmer and X. Wang are with the Dept of Applied Maths & Theoretical Physics, University of Cambridge, Wilberforce Rd, Cambridge, CB3 0WA, United Kingdom (sgs29@cam.ac.uk, xw233@cam.ac.uk).

F.T. acknowledges support by the CPDA080209/08 and “Quantum Future” research grants of the University of Padova, and by the Department of Information Engineering research project “QUINTET”. SGS acknowledges funding from EPSRC ARF Grant EP/D07192X/1 and Hitachi.

with off-diagonal elements determined by the spectrum of ρ . The diagonal elements a_n and h_n of L and H are free variables. Further analysis shows that ρ is GAS for most all choices of the diagonal elements a_n and h_n , and we give explicit conditions on h_n to guarantee GAS of ρ .

In Section III, we illustrate by an example how the Lindblad generator L obtained this way can be implemented by reservoir engineering via direct (Markovian) feedback [9], [10], [11], [12], where the controlled dynamics has the form of a Wiseman-Milburn Markovian *Feedback Master Equation* (FME)[9], [13]:

$$\dot{\rho}_t = -i[H + H_C + \frac{1}{2}(FM + M^\dagger F), \rho_t] + \mathcal{D}(M - iF, \rho_t) + \mathcal{D}(L_0, \rho_t). \quad (2)$$

The drift Hamiltonian $H \in \mathfrak{H}(\mathcal{H})$, the measurement operator $M \in \mathfrak{B}(\mathcal{H})$ and the noise operator L_0 are assumed to be given, while the open-loop and the feedback Hamiltonians $H_C, F \in \mathfrak{H}(\mathcal{H})$ are our control parameters.

II. MAIN RESULTS

A. Preliminaries and design assumptions

We recall two results on subspace stabilization that have been derived in [7], [8], which will be used in the rest of the paper.

Theorem 1 (Feedback-attractive subspaces [7]): Let $\mathcal{H}_I = \mathcal{H}_S \oplus \mathcal{H}_R$ with Π_S being the orthogonal projection on $\mathcal{H}_S$. If we can freely choose both the open-loop and the feedback Hamiltonian then, for any measurement operator M , there exist a feedback Hamiltonian F and a Hamiltonian compensation H_C that make the subsystem supported by $\mathcal{H}_S$ invariant and attractive for the FME (2) iff

$$[\Pi_S, (M + M^\dagger)] \neq 0. \quad (3)$$

A constructive proof is provided in [7]. We will also make use of the following characterization of the global attractivity of a state:

Theorem 2 (Uniqueness equivalent to GAS [8]): A steady state of (1) is GAS if and only if it is unique.

Finally, we require a few basic observations and a simple lemma. Consider an orthogonal decomposition $\mathcal{H} = \mathcal{H}_S \oplus \mathcal{H}_R$ with $d_s = \dim(\mathcal{H}_S)$, $d_r = \dim(\mathcal{H}_R)$, and let $\{\phi_j^S\}_{j=1}^{d_s}, \{\phi_l^R\}_{l=1}^{d_r}$ be orthonormal bases for $\mathcal{H}_S, \mathcal{H}_R$, respectively. The basis

$$\{|\varphi_m\rangle\} = \{|\phi_j^S\rangle\}_{j=1}^{d_s} \cup \{|\phi_l^R\rangle\}_{l=1}^{d_r},$$

induces a block decomposition for matrices representing operators acting on $\mathcal{H}$:

$$X = \begin{bmatrix} X_S & X_P \\ X_Q & X_R \end{bmatrix}, \quad (4)$$

and we have the following:

Lemma 1: Assume $\rho = \begin{bmatrix} \rho_S & 0 \\ 0 & \rho_R \end{bmatrix}$, divided in blocks accordingly to some orthogonal Hilbert space decomposition $\mathcal{H} = \mathcal{H}_S \oplus \mathcal{H}_R$. Then ρ is invariant for the dynamics (1) if and only if:

$$0 = -i[H_S, \rho_S] + L_S \rho_S L_S^\dagger - \frac{1}{2}\{L_S^\dagger L_S, \rho_S\} + L_P \rho_R L_P^\dagger - \frac{1}{2}\{L_Q^\dagger L_Q, \rho_S\} \quad (5a)$$

$$0 = -i(H_P \rho_R - \rho_S H_P) + L_S \rho_S L_Q^\dagger - \frac{1}{2}\rho_S (L_S^\dagger L_P + L_Q^\dagger L_R) + L_P \rho_R L_R^\dagger - \frac{1}{2}(L_S^\dagger L_P + L_Q^\dagger L_R) \rho_R \quad (5b)$$

$$0 = -i[H_R, \rho_R] + L_R \rho_R L_R^\dagger - \frac{1}{2}\{L_R^\dagger L_R, \rho_R\} + L_Q \rho_S L_Q^\dagger - \frac{1}{2}\{L_P^\dagger L_P, \rho_R\} \quad (5c)$$

Proof: By direct computation of the generator (1) one finds its S, P and R -blocks to be the l.h.s. of (5a)-(5c), respectively. A given state ρ is stationary if and only if $\mathcal{L}(\rho) = 0$, and hence if and only if its blocks are all zero. ■

We know from [6], [7] that for ρ to be invariant, its support $\mathcal{H}_\rho$ must be an invariant subspace, and using the constructive procedure used in

the proof of Theorem 1, we can construct an block-upper-triangular L that stabilizes the $\mathcal{H}_\rho$ subspace. There are many possible choices to do that, e.g.

$$L = \left[\begin{array}{c|c} L_\rho & L_{\rho,P} \\ \hline 0 & L_{\rho,R} \end{array} \right]$$

with blocks

$$L_{\rho,P} = \begin{bmatrix} 0 & 0 & \dots & 0 \\ \vdots & 0 & \dots & 0 \\ \ell_1 & 0 & \dots & 0 \end{bmatrix}, \quad L_{\rho,R} = \begin{bmatrix} 0 & \ell_2 & 0 & 0 \\ 0 & 0 & \ell_3 & \ddots \\ \vdots & & \ddots & \ddots \end{bmatrix}$$

with $\ell_1, \ell_2, \dots \neq 0$. Therefore, we can focus on the dynamics restricted to the invariant support $\mathcal{H}_\rho$, and restrict our attention here to full-rank states $\rho = \text{diag}(p_1, \dots, p_N)$ with $p_1, \dots, p_N > 0$. To develop a constructive procedure to build a stabilizing pair (H, L) with a simple structure we make a series of assumptions and design choices:

Assumption 1. The spectrum of ρ is non-degenerate (generic case). A state with non-degenerate spectrum can be chosen arbitrarily close to any state. Without loss of generality, we can choose a basis such that ρ is diagonal $\rho = \text{diag}(p_1, \dots, p_N)$ with $p_1 > \dots > p_N > 0$. This assumption is instrumental for the construction of L but can actually be relaxed, as we remark after the Theorem 3. Consider the decomposition $\mathcal{H} = \mathcal{H}_S \oplus \mathcal{H}_R$, with $\dim(\mathcal{H}_R) = 1$, such that the corresponding block decomposition for ρ is $\rho = \begin{bmatrix} \rho_S & 0 \\ 0 & \rho_R \end{bmatrix}$, and divide accordingly H, L .

Assumption 2. ρ_S satisfies

$$-i[H_S, \rho_S] + L_S \rho_S L_S^\dagger - \frac{1}{2}\{L_S^\dagger L_S, \rho_S\} = 0. \quad (6)$$

Condition (6) is clearly not satisfied in general, but it will be ensured at each step of the iterative procedure outlined in the next Section. Given this, conditions (5a)-(5c) can be rewritten as:

$$\begin{cases} 0 = L_Q \rho_S L_Q^\dagger - \rho_R L_P^\dagger L_P \\ 0 = L_P \rho_R L_P^\dagger - \frac{1}{2}\{L_Q^\dagger L_Q, \rho_S\}. \end{cases} \quad (7)$$

Since we assumed $\mathcal{H}_R$ to be one-dimensional, L_P and $L_Q^\dagger$ are both $n-1$ dimensional vectors. Call $\Pi_P = L_P L_P^\dagger / (L_P^\dagger L_P)$, $\Pi_Q = L_Q^\dagger L_Q / (L_Q L_Q^\dagger)$. Then the second equation in (7) reads:

$$\rho_R (L_P^\dagger L_P) \Pi_P = (L_Q L_Q^\dagger) \frac{1}{2} (\Pi_Q \rho_S + \rho_S \Pi_Q). \quad (8)$$

Assumption 3. Choose Π_Q to be the orthogonal projector on the eigenspace corresponding to the smallest eigenvalue of ρ_S .

Choose an ordered spectral decomposition with rank-one projectors, $\rho = \sum_{j=1}^{N-1} p_i \Pi_{S,i} + \rho_R \Pi_R$, where $p_i > p_{i+1}$. As ρ is in diagonal form this means that we are choosing:

$$L_Q = \begin{bmatrix} 0 & \dots & 0 & \ell_Q \end{bmatrix}.$$

We thus get:

$$\rho_R (L_P^\dagger L_P) \Pi_P = (L_Q L_Q^\dagger) p_{N-1} \Pi_Q, \quad (9)$$

which can be satisfied if and only if $\Pi_P = \Pi_Q$ and $\rho_R (L_P^\dagger L_P) = (L_Q L_Q^\dagger) p_{N-1}$. We can choose $L_P^\dagger L_P = p_{N-1}$, obtaining $(L_Q L_Q^\dagger) = p_N$. Hence ℓ_Q can be in particular chosen to be real, $\ell_Q = \sqrt{p_N}$. We have thus constructed a Lindblad term of the form:

$$L = \left[\begin{array}{c|c} L_S & \begin{bmatrix} 0 \\ \vdots \\ 0 \end{bmatrix} \\ \hline \begin{bmatrix} 0 & \dots & 0 \end{bmatrix} & \begin{bmatrix} \sqrt{p_{N-1}} \\ L_R \end{bmatrix} \end{array} \right].$$

As ρ_R is a scalar, we can rewrite (5b) as:

$$-i(\rho_R I_S + \rho_S) H_P + K = 0, \quad (10)$$

where $K = -\frac{1}{2}(L_P L_R^\dagger + L_S^\dagger L_P + L_Q^\dagger L_R) \rho_R - \frac{1}{2} \rho_S (L_S^\dagger L_P + L_Q^\dagger L_R) + L_S \rho_S L_Q^\dagger$. Once $\rho_S, \rho_R, L_S, L_R, L_P, L_Q$ are fixed, (10) is a linear system in H_P which always admits a unique solution $H_P = i(\rho_R I_S + \rho_S)^{-1} K$, which is a necessary condition for the invariance of ρ . We are now in a position to present an inductive procedure for constructing stabilizing generators.

B. Constructive algorithm and proof of uniqueness

We start by constructing a stabilizing generator for the two-level case. Let $\rho = \begin{bmatrix} p_1 & 0 \\ 0 & p_2 \end{bmatrix}$ with $p_1 > p_2 > 0$. Note that in the reasoning of the previous Section it is not necessary to impose $\text{tr}(\rho) = 1$. We will make use of this fact in extending the procedure to the n -dimensional case.

Given the previous observations, we can render the given ρ invariant for the dynamics if we can enact dissipation driven by a Lindblad operator and a Hamiltonian of the form

$$L = \begin{bmatrix} a_1 & \sqrt{p_1} \\ \sqrt{p_2} & a_2 \end{bmatrix} \quad (11)$$

and a H such that its off-diagonal elements satisfy (10).

In the N -level case let $\rho = \text{diag}(p_1, \dots, p_N)$. We can iterate our procedure by induction on the dimension of $\mathcal{H}_S$. We have just found the 2×2 upper-left blocks of L and H such that $\rho^{(2)} = \text{diag}(p_1, p_2)$ is stable and attractive for the dynamics driven by the reduced matrices. Assume that we have some $m \times m$ upper-left blocks of L and H such that $\rho^{(m)} = \text{diag}(p_1, \dots, p_m)$ is invariant for the reduced dynamics. This is exactly Assumption 2 above. Let $\mathcal{H}_S^{(m)} = \text{supp}(\sum_{j=1}^m p_j \Pi_j)$, $\mathcal{H}_R^{(m)} = \text{supp}(p_{m+1} \Pi_{m+1})$. If we want to stabilize $\rho^{(m+1)} = \text{diag}(p_1, \dots, p_{m+1})$ for the dynamics restricted to $\mathcal{H}_S^{(m)} \oplus \mathcal{H}_R^{(m)}$, we can then proceed building $L_Q^{(m)}, L_P^{(m)}$ using Design Choice 1 above. Design Choice 2 lets us compute the off-diagonal terms of the Hamiltonian, while we can pick H_R to assume any value, since it does not enter the procedure.

By iterating until $m = N$, we obtain a tridiagonal matrix L with $L_{n,n+1} = \sqrt{p_n}$, $L_{n+1,n} = \sqrt{p_{n+1}}$ and $L_{n,n} = a_n$, i.e.,

$$L = \begin{bmatrix} a_1 & \sqrt{p_1} & 0 & \dots & 0 & 0 \\ \sqrt{p_2} & a_2 & \sqrt{p_2} & \dots & 0 & 0 \\ 0 & \sqrt{p_3} & a_3 & \dots & 0 & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & 0 & \dots & \sqrt{p_{N-1}} & a_{N-1} & \sqrt{p_{N-1}} \\ 0 & 0 & \dots & 0 & \sqrt{p_N} & a_N \end{bmatrix} \quad (12)$$

and H becomes a quintdiagonal Hermitian matrix, i.e.,

$$\begin{aligned} H_{nn} &= h_n, \\ H_{n,n+1} &= H_{n+1,n}^* = \frac{i}{2} \frac{\sqrt{p_n} - \sqrt{p_{n+1}}}{\sqrt{p_n} + \sqrt{p_{n+1}}} (a_n \sqrt{p_n} + a_{n+1} \sqrt{p_{n+1}}) \\ H_{n,n+2} &= H_{n+2,n}^* = -\frac{i}{2} p_{n+1} \frac{\sqrt{p_n} - \sqrt{p_{n+2}}}{\sqrt{p_n} + \sqrt{p_{n+2}}}, \end{aligned} \quad (13)$$

Theorem 3: If (H, L) are chosen as in (12-13) then $\rho = \text{diag}(p_1, \dots, p_N)$ is a stationary state of the LME $\dot{\rho}(t) = -i[H, \rho] + \mathcal{D}(L, \rho)$. ρ is GAS for most choices of the diagonal elements $\mathbf{a}$ and $\mathbf{h}$ of L and H , respectively; in particular there exists $M_0 \geq 0$ so that ρ is GAS for $\mathbf{h} = (M, 0, \dots, 0)$ for all $M > M_0$.

Proof: Given the generator, we can verify by direct calculation that ρ is a steady state. Setting $B = \mathcal{D}(L, \rho)$, direct calculation shows that $B_{m,n} = 0$ except for

$$B_{n,n+1} = B_{n+1,n} = -\frac{1}{2}(\sqrt{p_n} - \sqrt{p_{n+1}})^2(d_n\sqrt{p_n} + d_{n+1}\sqrt{p_{n+1}}),$$

$$B_{n,n+2} = B_{n+2,n} = -\frac{1}{2}p_{n+1}(\sqrt{p_n} - \sqrt{p_{n+1}})^2,$$

and setting $A = i[H, \rho]$ shows that the Hamiltonian term exactly cancels the non-zero elements of B , i.e., $-A + B = 0$. Thus ρ is a steady state of the system.

To show how to make ρ the unique, and hence attractive, stationary state, assume that ρ' is another stationary state in the support of ρ . Let $\mathcal{X} = \{X | X = x\rho + y\rho', x, y \in \mathbb{R}\}$. Then any state in $\mathcal{X} \cap \mathcal{D}(\mathcal{H})$ is also stationary. Since $\mathcal{X}$ is unbounded while $\mathcal{D}(\mathcal{H})$ is compact, there must be a stationary state ρ_1 at the boundary of $\mathcal{D}(\mathcal{H})$, i.e., with rank strictly less than ρ . Then the support of ρ_1 , $\mathcal{H}_1 = \text{supp}(\rho_1)$, must be invariant [7], and H, L must exhibit the following block-decompositions with respect to the orthogonal decomposition $\mathcal{H} = \mathcal{H}_1 \oplus \mathcal{H}_2$:

$$H = \begin{bmatrix} H_{11} & H_{12} \\ H_{12}^\dagger & H_{22} \end{bmatrix}, \quad L = \begin{bmatrix} L_{11} & L_{12} \\ 0 & L_{22} \end{bmatrix},$$

with $H_{12} = -i\frac{1}{2}L_{11}^\dagger L_{12}$. If $L_{12} \neq 0$ then it is straightforward to show that $\text{Tr}(\Pi_2 \rho)$, where Π_2 the orthogonal projection onto $\mathcal{H}_2$, is strictly decreasing [6], and thus $\mathcal{H}_2$ is not invariant. Since ρ is also stationary, and is a full-rank state, this is not possible and we must therefore have $L_{12} = 0$ and thus $H_{12} = 0$. This implies that H and L are block-diagonal. Both $\mathcal{H}_1$ and $\mathcal{H}_2$ must contain at least one eigenvector of L , say $\mathbf{v}_1$ and $\mathbf{v}_2$. Orthogonality of the subspaces $\mathcal{H}_1$ and $\mathcal{H}_2$ along with the block-decomposition of H and L imply that any pair of vectors $\mathbf{v}_1 \in \mathcal{H}_1$, $\mathbf{v}_2 \in \mathcal{H}_2$ must satisfy:

$$\mathbf{v}_2^\dagger L \mathbf{v}_1 = \mathbf{v}_2^\dagger H \mathbf{v}_1 = \mathbf{v}_2^\dagger \mathbf{v}_1 = 0. \quad (14)$$

These are *necessary condition* the existence of another stationary state, and hence for making ρ not attractive.

From the results in the appendix (Theorem 7), a tridiagonal L in the form (12) has n distinct eigenvalues corresponding to n eigenvectors $\mathbf{v}_k$ with real entries and the first all different from zero. Without loss of generality, we can assume that the first element of each (unnormalized) eigenvector $\mathbf{v}_j$ equals 1 for all j . If the eigenvectors are mutually non-orthogonal, i.e., $\mathbf{v}_k^\dagger \mathbf{v}_\ell \neq 0$ for all k, ℓ then the third equality in (14) is automatically violated, and hence ρ must be the unique stationary state. This condition will almost always be satisfied in practice, and it is easy to check that it is always true when $N = 2$ (see appendix). However, even if L has orthogonal eigenvectors we can use our freedom of choice in the diagonal elements h_{nn} of H to render ρ the unique stationary state.

Assume $\mathbf{v}_j^\dagger \mathbf{v}_k = 0$ for some pair of eigenvectors of L . Let H_0 be the Hamiltonian corresponding to $\mathbf{h} = \mathbf{0}$ and $M_0 = \max_{j,k} |\mathbf{v}_j^\dagger H_0 \mathbf{v}_k|$. Choose $M > M_0$ and let H be the Hamiltonian corresponding to $\mathbf{h} = (M, 0, \dots)$, $H = H_0 + \text{diag}(M, 0, \dots, 0)$. Recalling that the first component of $\mathbf{v}_j$ is 1 for all j , shows that

$$\mathbf{v}_j^\dagger H \mathbf{v}_k = M + \mathbf{v}_j^\dagger H_0 \mathbf{v}_k > 0,$$

and therefore the second equality in (14) is violated, and ρ is the unique stationary state. ■

Remark: Theorem 3–7 further shows that Assumption 1 on the spectrum of ρ can be relaxed, since the fact that the spectrum is non-degenerate plays no role in the proof. The construction is effective for any full rank state on the desired support.

III. FEEDBACK STABILIZATION OF ENCODED QUBIT STATES

Consider a system whose evolution is governed by the FME (2) with $H_0 = -H_C'$, $M = M^\dagger$, and L admitting an eigenspace $\mathcal{H}_S$ of dimension 2 for some eigenvalue λ_S . Assume we can switch off the measurement and the feedback Hamiltonian, $F = M = 0$. With this choice, (2) admits a two-dimensional *noiseless (or decoherence-free) subspace* [14], [15], [6], which can be effectively used to encode a quantum bit protected from noise. We now face the problem of *initializing* the quantum state *inside the DFS*: we thus wish to construct H_C , F and M , such that a given state ρ of the *encoded qubit* is GAS on the full Hilbert space. Setting $\mathcal{H} = \mathcal{H}_S \oplus \mathcal{H}_R$ and choosing an appropriate basis for $\mathcal{H}_S$, the encoded state to be stabilized takes the form

$$\rho = \begin{bmatrix} \rho_S & 0 \\ 0 & 0 \end{bmatrix}, \quad \rho_S = \begin{bmatrix} p_1 & 0 \\ 0 & p_2 \end{bmatrix}.$$

The dynamical generators can be partitioned accordingly,

$$L = \begin{bmatrix} \lambda_M I_2 & L_P \\ 0 & L_R \end{bmatrix}, \quad H_C = \begin{bmatrix} H_S & H_P \\ H_P^\dagger & H_R \end{bmatrix},$$

$$F = \begin{bmatrix} F_S & F_P \\ F_P^\dagger & F_R \end{bmatrix}, \quad M = \begin{bmatrix} M_S & M_P \\ M_P^\dagger & M_R \end{bmatrix}$$

where I_2 is the 2×2 identity matrix. We compensate the feedback-correction to the Hamiltonian by choosing $H_C = H_C' - \frac{1}{2}(FM + M^\dagger F)$. For $L_P \neq 0$ we use the constructive algorithm described above to render $\mathcal{H}_S$ attractive by choosing $F_P = -iM_P$, and constructing a H_R' for H_C' so that no invariant state has support in $\mathcal{H}_R$ (see Theorem 12 in [7]) and by imposing $H_P' = 0$. For $L_P = 0$ we need to choose an observable such that $M_P \neq 0$. We are thus left with freedom on the choice of H_S, F_S , which can be now used to stabilize the desired ρ_S in the controlled invariant subspace $\mathcal{H}_S$. Denote the elements of the upper-left 2×2 blocks as

$$M_S = \begin{bmatrix} M_1 & M_3 \\ M_3^\dagger & M_2 \end{bmatrix}, \quad F_S = \begin{bmatrix} F_1 & F_3 \\ F_3^\dagger & F_2 \end{bmatrix} \quad (15)$$

Set $F_3 = -\frac{ik_M}{2}(\sqrt{p_2} - \sqrt{p_1})$. If $M_3 \neq 0$, setting $k_M := 2M_3/(\sqrt{p_1} + \sqrt{p_2})$ shows that $M_3 = \frac{k_M}{2}(\sqrt{p_1} + \sqrt{p_2})$, i.e., up to the multiplicative constant k_M the two block matrices are such that $M_S - iF_S$ is of the form (12), Theorem 3 applies and the desired state is GAS. Notice that if $M_3 = 0$, and M has non-degenerate spectrum, it is easy to find another state ρ' , arbitrarily close to ρ , such that, in the basis in which ρ' is diagonal, we have $M_3' \neq 0$. Thus we can attain practical stabilization of any state of the encoded qubit.

IV. CONCLUSIONS AND OUTLOOK

Efficient quantum state preparation is crucial to most of the physical implementations of quantum information technologies. Here we have shown how *quantum noise* can be designed to stabilize arbitrary quantum states. The main interest in such a result is motivated by direct feedback design for applications in quantum optical and optomechanical systems and quantum information processing applications. As an example we have demonstrated how to devise the (open- and closed- loop) control Hamiltonians in order to asymptotically stabilize a state of a qubit encoded in a noiseless subspace of a larger system. Further study is under way to address similar problems for multiple qubits, in the presence of structural constraints on the measurements, control and feedback operators, and to optimize the speed of convergence to the target state.

ACKNOWLEDGMENTS

We thank Arie Iserles, Lorenza Viola and Maria Jose Cantero for interesting and fruitful discussions.

APPENDIX

We collect here results about orthogonal polynomials and tridiagonal matrices that are instrumental to the proof of Theorem 3. Details and (missing) proofs can be found in [16], [17], [18].

Definition 1: An orthogonal polynomial sequence $\{P_n(x)\}_{n=1}^\infty$ over $[a, b] \subset \mathbb{R}$ is an infinite sequence of real polynomials such that $\langle P_j, P_k \rangle = 0$ for any $j \neq k$ under some L^2 inner product $\langle P_j, P_k \rangle := \int P_j(x)P_k(x)w(x)dx$ with a weighing function $w(x)$.

Theorem 4 (Favard [16]): A monic polynomial sequence $\{P_n(x)\}$ is an orthogonal polynomial sequence if it satisfies a three-term recurrence relation

$$P_{n+1}(x) = (x - b_n)P_n(x) - c_n P_{n-1}(x), n \geq 0 \quad (16)$$

with $\{b_n\}, \{c_n\}$ sequences of real numbers and $c_n > 0$.

Theorem 5 ([17]): If $\{P_n(x)\}$ is a sequence of orthogonal polynomials then each $P_n(x)$ has n distinct roots.

Theorem 6: A real-symmetric tridiagonal $N \times N$ matrix with non-zero entries on the first sub/superdiagonal has N distinct eigenvalues.

Proof: It suffices to note that the monic polynomial sequence $\{f_n\}$ with $f_0(\lambda) = 1$ and

$$f_n(\lambda) = \det \begin{bmatrix} \lambda - \alpha_1 & \beta_1 & 0 & \dots & 0 \\ \beta_1 & \lambda - \alpha_2 & \beta_2 & & \vdots \\ 0 & & \ddots & & \\ \vdots & \vdots & & & \\ 0 & \dots & 0 & \beta_{n-1} & \lambda - \alpha_n \end{bmatrix} \quad (17)$$

for $n = 1, 2, \dots, N$ satisfies the recurrence relation

$$f_{n+1}(\lambda) = (\lambda - \alpha_{n+1})f_n(\lambda) - \beta_n^2 f_{n-1}(\lambda) \quad (18)$$

and therefore is an orthogonal polynomial sequence by Favard's theorem provided $\beta_n^2 > 0$. Thus $f_n(\lambda)$ has n distinct roots for all n , and the matrix has N distinct eigenvalues. ■

The expression for the corresponding (unnormalized) eigenvectors $\tilde{v}_k$ can then be obtained by straightforward calculation:

$$\tilde{v}_{jk} := \frac{f_{j-1}(\lambda_k)}{\beta_1 \dots \beta_{j-1}}. \quad (19)$$

Theorem 7: Let T be a real tridiagonal matrix. If $T_{n,n+1} = \beta_n > 0$ and $T_{n+1,n} = \gamma_n > 0$ then T has N distinct eigenvalues λ_n .

Proof: There always exists a diagonal matrix $D = \text{diag}(d_n)$ such that $S = D^{-1}TD$ is a symmetric tridiagonal matrix: the diagonal elements must satisfy $d_{n+1}^2 = d_n^2 \gamma_n / \beta_n$ for all n , which shows that D is uniquely determined up to global factor. We fix $d_n = 1$. The off-diagonal elements of S are $S_{n,n+1} = S_{n+1,n} = \sqrt{\beta_n \gamma_n}$. The matrix S is real-symmetric and hence $S = VE V^\dagger$, with $E = \text{diag}(\lambda_n)$. By the previous theorem the eigenvalues λ_n are real and distinct provided $\beta_n \gamma_n > 0$ for all n . V is a real-orthogonal matrix whose columns are the normalized eigenvectors of S , $\mathbf{v}_k = C_k^{-1} \tilde{\mathbf{v}}_k$ with $\mathbf{v}_{jk}$ as defined in (19) and $C_k = \|\tilde{\mathbf{v}}_k\|$. Since $T = DSD^{-1} = D(VEV^\dagger)D^{-1} = (DV)E(DV)^{-1}$, T has the same eigenvalues as S , with eigenvectors $\mathbf{w}_k = D\mathbf{v}_k$. ■

While it is not strictly needed for the result in this work, it is worth noticing that for almost all choices of diagonal entries in T , the eigenvectors will be mutually non-orthogonal unless T is symmetric. For fixed off-diagonal elements β_k and γ_k , the eigenvalues λ_k and corresponding eigenvectors $\mathbf{v}_k$ of S can be expressed explicitly in terms of the diagonal entries $\mathbf{a}$. Since $f_N(\lambda, \mathbf{a})$ is an N th order polynomial in λ with N distinct roots, by the implicit function theorem, all roots λ_k for $f_N(\lambda, \mathbf{a}) = 0$ can be expressed locally as continuously-differentiable functions $\lambda_k(\mathbf{a})$ in some open

neighborhood $\mathcal{N}_\mathbf{a}$ of $\mathbf{a}$, and similarly for the eigenvectors $\mathbf{v}_k$. To determine whether $T(\alpha)$ has orthogonal eigenvectors consider the functions

$$F_{k\ell}(\alpha) = \sum_{n=1}^{N-1} d_n^2 b_{n-1}^2 f_{n-1}(\lambda_k(\alpha)) f_{n-1}(\lambda_\ell(\alpha)) \quad (20)$$

which correspond to the inner products of the unnormalized eigenvectors of T with $b_n = (\beta_1 \dots \beta_n \gamma_1 \dots \gamma_n)^{-1}$. By orthogonality of the eigenvectors of S we have

$$B_{k\ell} = \sum_{n=1}^{N-1} b_{n-1}^2 f_{n-1}(\lambda_k(\alpha)) f_{n-1}(\lambda_\ell(\alpha)) \quad (21)$$

for all α . But $F_{k\ell}$ and $G_{k\ell}$ are polynomials in λ and α and differ only by the coefficient d_n . Thus, we will have $F_{k\ell}(\alpha) \neq G_{k\ell}(\alpha)$ for most α unless all d_n are equal, which implies $\beta_n = \gamma_n$ for all n and T symmetric. (In our case this would only happen when all populations p_n are equal.) By continuity of $F_{k\ell}(\alpha)$ we can conclude that in any neighborhood $\mathcal{N}_{\alpha_0}$ of a bad point α_0 with $F_{k\ell}(\alpha_0) = 0$, there is an open (and thus positive-measure) subset of points with $F_{k\ell}(\alpha) \neq 0$, provided $F_{k\ell}(\alpha)$ is not constant on $\mathcal{N}_{\alpha_0}$. This argument can be made stronger and more rigorous if we assume $\frac{\partial F_{k\ell}(\alpha)}{\partial \alpha_m}(\alpha_0) \neq 0$ for some α_m , i.e., that not all partial derivatives at the bad point α_0 vanish, in which case we can show that $F_{k\ell}(\alpha)$ vanishes only on a measure-zero subset of $\mathcal{N}_{\alpha_0}$ using the implicit function theorem.

REFERENCES

- [1] G. Lindblad. On the generators of quantum dynamical semigroups. *Communication in Mathematical Physics*, 48(2):119–130, 1976.
- [2] V. Gorini, A. Kossakowski, and E.C.G. Sudarshan. Completely positive dynamical semigroups of n -level systems. *Journal of Mathematical Physics*, 17(5):821–825, 1976.
- [3] H. K. Khalil. *Nonlinear Systems*. Prentice Hall, USA, third edition, 2002.
- [4] L. Viola, E. Knill, and R. Laflamme. Constructing qubit in physical systems. *Journal of Physics A*, (34):7067–7079, 2001.
- [5] M. A. Nielsen and I. L. Chuang. *Quantum Computation and Information*. Cambridge University Press, Cambridge, 2002.
- [6] F. Ticozzi and L. Viola. Quantum Markovian subsystems: Invariance, attractivity and control. *IEEE Transaction on Automatic Control*, 53(9):2048–2063, 2008.
- [7] F. Ticozzi and L. Viola. Analysis and synthesis of attractive quantum Markovian dynamics. *Automatica*, 45:2002–2009, 2009.
- [8] S. G. Schirmer and Xiaoting Wang. Stabilization of Quantum States by Markovian Reservoir Engineering via Direct Quantum Feedback, *Physical Review A*, 81:062306:1–14, 2010.
- [9] H. M. Wiseman. Quantum theory of continuous feedback. *Physical Review A*, 49(3):2133–2150, 1994.
- [10] J. Wang and H. M. Wiseman. Feedback-stabilization of an arbitrary pure state of a two-level atom. *Physical Review A*, 64(6):063810:1–9, 2001.
- [11] S. Mancini, D. Vitali, and P. Tombesi. Optomechanical cooling of a macroscopic oscillator by homodyne feedback. *Physical Review Letters*, 80(4):688–691, 1998.
- [12] A. Barchielli and M. Gregoratti. *Quantum Trajectories and Measurements in Continuous Time: The Diffusive Case*. Lecture Notes in Physics, 782 Springer, Berlin Heidelberg, 2009.
- [13] H. M. Wiseman and G. J. Milburn. Quantum theory of optical feedback via homodyne detection. *Physical Review Letters*, 70(5):548–551, 1993.
- [14] D. A. Lidar, I. L. Chuang, and K. B. Whaley, “Decoherence-free subspaces for quantum computation,” *Physical Review Letters*, vol. 81, no. 12, pp. 2594–2597, 1997.
- [15] A. Shabani and D. A. Lidar. Theory of initialization-free decoherence-free subspaces and subsystems. *Physical Review A*, 72(4):042303:1–14, 2005.
- [16] F. Marcellan, and R. Alvarez-Nodarse. On the “Favard theorem” and its extensions. *Journal of Computational and Applied Mathematics archive*, 127, 1-2, 2001.
- [17] V. Totik, Orthogonal Polynomials, *Surveys in Approximation Theory*, 1, 70-125, 2005.
- [18] T. S. Chihara, An Introduction to Orthogonal Polynomials, Routledge, London, 1978.